

**ZN3-77-04-TP
Highly Flexible “Quick Fit”
Substitute UHF CB Antenna Top**

Frequency
477 MHz

Gain
2.1 dBi



For owners of our large high gain ZN3 bull bar mount 477 MHz UHF CB antennas, ZN3-77-04-TP is the perfect substitute antenna top. When travelling into bush areas where a tall antenna might be subject to damage, or in city areas where high gain is not necessary, then simply interchange your antenna top with this convenient 40 cm “Quick Fit” 2.1 dBi model.

Key features of the antenna top include :

- The UHF male connector inside the base fits directly onto any of the spring bases supplied with our **ZN3-77-12**, **ZN3-77-11** or **ZN3-77-10** bull bar mount 477 MHz UHF CB radio antennas.
- The black delrin and UV stabilised PVC antenna top is highly flexible and virtually unbreakable. It will survive hard knocks and the the roughest treatment.
- The antenna is a small size for easy storage inside your vehicle, inexpensive and offers adequate performance with 2.1 dBi gain.
- The “Quick Fit” interchange of antenna tops takes less than a minute !
- The antenna comes factory tuned for 477 MHz UHF CB radio. Simply fit and use.
- The precision machined delrin ferrule prevents water and dust ingress giving the antenna a longer service life.



SPECIFICATIONS	ZN3-77-04-TP
Construction	Highly flexible UV stabilised black PVC top, UHF male connector inside “Quick Fit” black delrin base
Frequency	477 MHz UHF CB Radio
VSWR	Less than 1.5:1
Tuning	Factory
Gain	2.1 dBi
Maximum Power	100 Watts
Impedance	50 Ohms
Polarisation	Vertical
H-Plane	360° Omnidirectional
Height and Weight	40 cm, 200 grams
Mounting	This interchangeable antenna top will “Quick Fit” directly onto the spring bases supplied with these ZCG Scalar bull bar mount antenna models : <ul style="list-style-type: none"> ➤ ZN3-77-12 Super Heavy Duty, 2.1 metre, 8.1 dBi ➤ ZN3-77-11 Heavy Duty, 1.2 metre, 6.6 dBi ➤ ZN3-77-10 Medium Duty, 1.1 metre, 6.6 dBi
Compatible spring bases available to order separately	<ul style="list-style-type: none"> ➤ ZN3-SB-L, or ➤ ZNS-SB-S Installation kit includes 4.5 metre RG58 cable, UHF male connector, solder, cable ties, PVC cap



Step 1.
Remove your original ZN3 antenna top using the Allen Hex Key supplied in the kit.

Store the antenna top in a safe place.



Step 2.
Screw the **ZN3-77-04-TP** “Quick Fit” antenna top onto the UHF female connector on the spring base.

Installation is complete. Nothing could be simpler !